



**WACKER
NEUSON**
all it takes!

GP4000A

5100070504

[Home](#) >> [Catalog](#) >> [Products](#) >> [Power supply](#) >> [Portable Generators](#) >> [GP4000A](#)

GP4000A

Material number 5100070504



Portable generator power designed for construction applications or anywhere high performance, reliable power is needed.

Product details

- Powered by Honda
- Top Quality Alternator
- Efficient Voltage Regulation

Comes with

- Operator's Manual

Technical specifications

GP4000A

GENERATOR	Imperial	Metric
Phase	1 ~	1 ~
Voltage accuracy	6,0 %	6,0 %
Continuous Output	3.800 W	3.800 W
Maximum Output	4.000 W	4.000 W
Voltage 1~	240 V, 120 V	240 V, 120 V
Efficiency factor 1~	1,00 cos	1,00 cos
Generator specification	Brushless	Brushless
Output frequency	60 Hz	60 Hz
Insulation class	H	H

OPERATING FLUIDS	Imperial	Metric
Run Time (Prime Load)	12,5 std	12,5 std
Fuel consumption (Prime load)	0,6 GPH US	2,4 L/Std

ENGINE	Imperial	Metric
Cylinder	1	1
Engine Manufacturer	Honda	Honda
Cylinder capacity	16,5 Inch ³	270 cm ³
Operating Engine speed	3.600 1/min	3.600 1/min
Kraftstofftyp	Gasoline	Gasoline
Oil filling max.	0,3 gal US	1,10 l
Starter type	Recoil starter	Recoil starter
Engine Designation	GX270	GX270
Engine type	Gasoline engine	Gasoline engine

ELECTRICAL SYSTEM	Imperial	Metric
--------------------------	----------	--------

Receptacle Type	NEMA5-20R,Duplex GFCI,125V,20A, NEMAL14-30R,TL,125/250V,30A, NEMAL5-30R,TL,125V,30A	NEMA5-20R,Duplex GFCI,125V,20A, NEMAL14- 30R,TL,125/250V,30A, NEMAL5- 30R,TL,125V,30A
Circuit Breaker Amperage AC	18 A	18 A
Number of Sockets	4	4
Breaker Switch On/Off	1 Pole	1 Pole

ENVIRONMENT DATA	Imperial	Metric
Sound level LpA	72,0 dB(A)	72,0 dB(A)

MECHANICAL DETAILS	Imperial	Metric
Operating weight	166,0 lb	75,3 kg
Length	20,6 "	523 mm
Dry Weight	117,9 lb	53,5 kg
Height	24,1 "	612 mm
Width	27,5 "	698 mm

Please Note

This product availability can vary from country to country. It is possible that information / products may not be available in your country. More detailed information on engine power can be found in the operator's manual; the started power may vary due to specific operating conditions. Subject to alterations and errors expected. Applicable also to illustrations.

Copyright © 2023 Wacker Neuson SE