

GP2500A 5100070503

Home >> Catalog >> Products >> Power supply >> Portable Generators >> GP2500A



GP2500A

Material number 5100070503

Portable generator power designed for construction applications or anywhere high performance, reliable power is needed.

Product details

- Powered by Honda
- •Top Quality Alternator
- •Efficient Voltage Regulation

Comes with

Operator's Manual

Errors and omissions are reserved. The information in this data sheet is based on present knowledge. However, this neither guarantees specific product features nor establishes a legally valid contractual relationship.

Technical specifications

GP2500A

GENERATOR	Imperial	Metric
Phase	1 ~	1 ~
Voltage accuracy	6,0 %	6,0 %
Continuous Output	2.250 W	2.250 W
Maximum Output	2.500 W	2.500 W
Voltage 1~	240 V, 120 V	240 V, 120 V
Efficiency factor 1~	1,00 cos	1,00 cos
Generator specification	Brushless	Brushless
Output frequency	60 Hz	60 Hz
Insulation class	Н	Н
OPERATING FLUIDS	Imperial	Metric
Run Time (Prime Load)	10,0 std	10,0 std
Fuel consumption (Prime load)	0,4 GPH US	1,4 L/Std
ELECTRICAL SYSTEM	Imperial	Metric
December 1 True	NEMA5-20R, Duplex GFCI, 125V, 20A	NEMA5-20R, Duplex
Receptacle Type	NEWAS-2011, Duplex Of CI, 1257, 20A	GFCI,125V,20A
Circuit Breaker Amperage AC	20 A	GFCI,125V,20A 20 A
	·	GFCI,125V,20A
Circuit Breaker Amperage AC	20 A	GFCI,125V,20A 20 A
Circuit Breaker Amperage AC Number of Sockets	20 A 2	GFCI,125V,20A 20 A 2
Circuit Breaker Amperage AC Number of Sockets Breaker Switch On/Off	20 A 2 1 Pole	GFCI,125V,20A 20 A 2 1 Pole
Circuit Breaker Amperage AC Number of Sockets Breaker Switch On/Off ENVIRONMENT DATA	20 A 2 1 Pole Imperial	GFCI,125V,20A 20 A 2 1 Pole Metric

Errors and omissions are reserved. The information in this data sheet is based on present knowledge. However, this neither guarantees specific product features nor establishes a legally valid contractual relationship.

Length	18,1 "	459 mm
Dry Weight	68,8 lb	31,2 kg
Height	18,8 "	477 mm
Width	23,9 "	607 mm

Please Note

This product availability can vary from country to country. It is possible that information / products may not be available in your country. More detailed information on engine power can be found in the operator's manual; the started power may vary due to specific operating conditions. Subject to alterations and errors expected. Applicable also to illustrations.

Copyright © 2023 Wacker Neuson SE